

# **AMP-FL8011-CB**

## **C-band**

### **Optical Fiber Amplifier**

### **Specifications**



2-1-15 Ohara, Fujimino, Saitama 356-8502, Japan  
Phone: +81-49-278-7829, Facsimile: +81-49-263-9328  
e-mail: [info@fiberlabs.co.jp](mailto:info@fiberlabs.co.jp)  
web: <https://www.fiberlabs-inc.com/>

## • Preparations before use

This machine is warranted from any failure in normal operation as the machine is fully inspected mechanically and electrically before shipment from the factory. As soon as you receive the cargo, unpack and make certain that the machine is not damaged in transit.

### 1. Included Items

The standard included items are as follows. If any missing items are found upon inspection, contact us immediately.

• Optical amplifier:	1 unit
• Power ON/OFF key:	2 pieces
• Power cord:	1 piece
• Spare fuse:	1 piece (stored in the fuse box of the AC inlet)
• Specifications (by these presents):	1 copy (or CD)
• Operation Manual:	1 copy (or CD)
• Programming Manual:	1 copy (or CD)
• Final Test Inspection Record:	1 copy

We recommend that the carton box and the inner corrugated boards should be kept with care to avoid damage in case of reuse for transfer to another location.

### 2. Acceptance Inspection

#### (1) Mechanical movement check

As to external appearance, movement of the switch, the pump on button, the adjust dial, and connectors, carry out inspection under the condition of being the power supply off to look for possible damage or trouble caused in transit.

#### (2) Operation check

When no trouble is found upon mechanical movement check, carry out operation test to check functions, followed by the instructions of Operation Manual.

#### (3) Upon finding damage or anomalies

If, during acceptance inspection, damage to the machine or anomalies in connection with the specifications is found, contact us immediately with details of the trouble.

• **Standard specifications**

Product No.	AMP-FL8011-CB			
	-22-W	-22	-19	-16
Signal Wavelength	1530 to 1560nm (DWDM)	1530 to 1560 nm		
Maximum Output Power *1	≥ +22 dBm	≥ +22 dBm	≥ +19 dBm	≥ +16 dBm
Gain *2	≥ 35 dB	≥ 40 dB	≥ 35 dB	≥ 30 dB
Noise Figure *2	≤ 6 dB			
Input/Output Optical Isolation	≥ 40 dB			
Amplifier control	ACC / ALC			
Monitor items	Output power / Pumping LD current / Pumping LD temperature / Case temperature / Input power *4 / Reflected power*4			
Safety function	Remote interlock			
	Interlock with input Alarm*4 / Interlock with Reflection from output port*4			
Remote control Interface	RS232C / IEEE488.1(GP-IB)			
Input/Output Fibers	Corning SMF28			
Optical Connectors	FC/PC standard			
Size *3	88(H)×260(W)×350(D)mm			
Operation Temperature	0 to 40 °C			
Storage Temperature	-10 to 60 °C			
Power consumption	≤ 30W			
Weight	≤ 5 kg			
Power Supply	AC 100 to 240V(50/60Hz)			
Laser Class (Maximum Output Power)	Class 3B Laser product (≤ 200mW)			Class 3B Laser product (≤ 80mW)

\*1: input power : > 0 dBm @ 1550 nm

\*2: input power : -30 dBm @ 1550 nm

\*3: not including protrusions

\*AMP-FL8011-CB-22-W is designed to obtain the best gain flatness for input signals of 1530~1560nm with total power of 0dBm.

Customization is available for different input/output signal conditions.

\*4: optional function

\* Including Input / Output isolator

• **Options**

Option 012	FC / Angled PC optical connector
Option 013	SC / PC optical connector
Option 014	SC / Angled PC optical connector
Option 091	Loss of input port interlock (Input power monitor) *1
Option 093	Reflection from output port interlock (Reflected power monitor)
Option 121	Rack mount kit *2
Option 122	Rack mount kit *3

\*1: The specification of Noise Figure is ≤ 6.5dB with Option 091. (standard spec. +0.5dB )

\*2: Size of the type with “Option 121” is 88(H)×440(W)×350(D) mm.

\*3: Size of the type with “Option 122” is 88(H)×260(W)×350(D) mm