

# **AMP-FL8222-SB-18-PM**

## **S-band Optical Fiber Amplifier Specifications**



2-1-15 Ohara, Fujimino, Saitama 356-8502, Japan  
Phone: +81-49-278-7829, Facsimile: +81-49-263-9328  
E-mail: [info@fiberlabs.com](mailto:info@fiberlabs.com)  
URL: <https://www.fiberlabs.com>

## • Preparations before use

This machine is warranted from any failure in normal operation as the machine is fully inspected mechanically and electrically before shipment from the factory. As soon as you receive the cargo, unpack and make certain that the machine is not damaged in transit.

### 1. Included Items

The standard included items are as follows. If any missing items are found upon inspection, contact us immediately.

• Optical amplifier:	1 unit
• Power ON/OFF key:	2 pieces
• Power cord:	1 piece
• Spare fuse:	1 piece (stored in the fuse box of the AC inlet)
• Specifications (by these presents):	1 copy ( or CD)
• Operation Manual:	1 copy ( or CD)
• Programming Manual:	1 copy ( or CD)
• Final Test Inspection Record:	1 copy

We recommend that the carton box and the inner corrugated boards should be kept with care to avoid damage in case of reuse for transfer to another location.

### 2. Acceptance Inspection

#### (1) Mechanical movement check

As to external appearance, movement of the switch, the pump on button, the adjust dial, and connectors, carry out inspection under the condition of being the power supply off to look for possible damage or trouble caused in transit.

#### (2) Operation check

When no trouble is found upon mechanical movement check, carry out operation test to check functions, followed by the instructions of Operation Manual.

#### (3) Upon finding damage or anomalies

If, during acceptance inspection, damage to the machine or anomalies in connection with the specifications are found, contact us immediately with details of the trouble.

• **Standard specifications**

Product No.	AMP-FL8222-SB-18-PM
Signal Wavelength	1470~1520nm
Maximum Output Power *1	$\geq +18$ dBm (+19dBm typ.) *1
Gain *2	20 dB typ. *2
Noise Figure *2	$\leq 7$ dB *2
Extinction Ratio	$\geq 20$ dB
Working axis	Slow axis (Fast axis blocked)
Amplifier control	ACC / ALC
Monitor items	Input power / Output power / Pumping LD current / Pumping LD temperature / Case temperature
Safety function	Remote interlock
	Interlock with input Alarm
Remote control Interface	RS232C / IEEE488.1(GP-IB)
Input/Output Fibers	PM1550
Optical Connectors *3	FC/PC standard*3
Size *4	88(H) $\times$ 430(W) $\times$ 350(D)mm*4
Operation Temperature	0~40 degreeC
Storage Temperature	-10~60 degreeC
Power consumption	< 50W
Weight	< 7 kg
Power Supply	AC 100-240V(50/60Hz)
Laser Class (Maximum Output Power)	Class 3B (< 200mW)

\*1: input power : > 0 dBm @ 1490 nm

\*2: input power : -30 dBm @ 1490 nm

\*3: slow axis is aligned to the connector key

\*4: not including protrusions

\* Including Input/Output isolator

• **Options**

Option 012	FC / Angled PC optical connector
Option 013	SC / PC optical connector
Option 014	SC / Angled PC optical connector
Option 093	Reflection from output port interlock (Reflected power monitor)
Option 121	Rack mount kit

\*1: Size of the type with “Option 121” is 88(H) $\times$ 430(W) $\times$ 350(D) mm.